Foot Candle Light Adaptor

Measures Foot Candle on your multimeter

With 0.1FC/1Lux resolution

Features:

- A low cost alternative to a full size meter with display. Simply plug into your multimeter for direct measurements in Foot candles or Lux.
- Photo diode sensor prolongs life and enables instrument to cover wide ranges
- Three ranges (5% accuracy): (0 to 5,000Fc)
- Banana plugs insert directly into your multimeter, switch to 200mV range and aim sensor for reading on your multimeter
- 1mV/Fc output
- CE approved; one year warranty
- Dims: 3.9 x 2 x 1"(100 x 50 x 25mm) Weight: 6.7oz (190g)
- Complete with sensor with 3.8ft (1.2m) cable, protective cap, and 9V battery



Specifications			
Model 401021			
Fc Ranges (res.)	0 to 200Fc (0.1)	200 to 2000Fc (1)	2000 to 5000Fc (10)
Output	1mV/Fc	0.1mV/1Fc	0.1mV/10Fc
Model 401020			
Lux Ranges (res.)	0 to 2000Lux (1)	2000 to 20,000Lux (10)	20,000 to 50,000Lux (100)
Output	0.1mV/1Lux	0.1mV/10Lux	0.1mV/100Lux
Accuracy	±(5% + 0.1mV)		
Dimensions/Weight	3.9 x 2 x 1" (100 x 50 x 25mm)/ 6.7oz (190g)		

Ordering Information:

401021 .....Foot Candle Light Adaptor
401021-NIST....Foot Candle Light Adaptor with NIST Certificate

CE 1 YEAR WARRANTY

Specifications subject to change without notice.
Copyright © 2007-2008 Extech Instruments Corporation. All rights reserved including the right of reproduction in whole or in part in any form.