Triple Output Power Supply



Features:

- Two independently adjustable 0 to 30V DC regulated power supplies plus a 5V DC (fixed) power supply
- Fine and coarse adjustments for accurate voltage and current settings
- Auto tracking
- Selectable independent, series and parallel operation
- Constant voltage and constant current operation
- Analog meter reading of voltage and current for each 30V supply
- Overload and reverse polarity protection
- Power requirements : 100V, 120V, 220V, 240V AC, 50/60Hz
- Includes test leads and owners manual

Specifications:

Voltage (Each 30V Supply)	Adjustable from 0 to 30V DC
Line and Load Regulation	≤ 0.01% + 3mV
Ripple and Noise	≤ 1mV RMS
Current (Each 30V Supply)	Adjustable from 0 to 3A
Line and Load Regulation	≤ 0.2% +3mA
Ripple Current	≤ 3mA RMS
5V Supply Regulation	Line : ≤ 5mV, Load : ≤ 10mV
Ripple and Noise	≤ 2mV RMS
Output Current	3A Max.
Dimensions/Weight	10" (W) × 53/4" (H) × 131/4" (D)/24 lbs

Part Number Table

Description	Part Number
PSU, Bench, 2 × 0 to 30V, 5V, 3A	72-6615

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.