EXTECH INSTRUMENTS
A FLIR COMPANY

Experience the Extech Advantage

PRODUCT DATASHEET

Non-Contact AC Voltage and Current Detector

Detects and pinpoints wide range Voltage and Current

With Sensitivity Adjustment

Features:

- The only two-in-one current/voltage detector designed for electrical testing
- Non-Contact AC current detection from 200mA to 1000A
- Non-Contact AC voltage detection from 12V to 600VAC
- Sensitivity adjustments to increase or reduce sensor trigger threshold
- Loud audible and bright visible sense detect indicators
- Current sensor detects current flow through shielded wires, conduit and metal circuit breaker/junction boxes
- Current function detects current flow of 400mA at 0.2" distance and at much greater distances for larger current flows
- Convenient pocket size with clip
- Dims/Wt: 7.6 x 1.2 x 0.9" (192 x 31 x 24mm) / 2.1oz (60g)
- Complete with four LR44 button batteries and pocket clip

Applications:

- Trace concealed wires in walls and floors
- Identify “hot” wires
- Trace current flow behind walls, in conduit, where voltage detection does not work
- Sensitivity high enough to trip on low voltage HVAC or similar signal levels

Check voltage in breakers

Ordering Information:

DVA30 .....Non-Contact AC Voltage and Current Detector

c UL us LISTED CE EN 61010-1 CAT III 600V

Specifications subject to change without notice.
Copyright © 2007-2008 Extech Instruments Corporation. All rights reserved including the right of reproduction in whole or in part in any form.

10/16/08 - R2

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Extech:
DVA30